



## **Quad Output DC Power Supply**

## 4-in-1 Power Supply

Four power supplies built into one — Two fully adjustable supplies combined with two auxiliary outputs

## **Features:**

- Two 0 to 30V/0 to 5A outputs with selectable Constant Voltage and Constant Current modes
- Outputs up to 60V in series mode or 10A in parallel mode
- Two auxiliary outputs with fixed current of 3 to 6.5V/3A and 8 to 15V/1A
- Overload and short circuit protection
- Complete with power cord and 4 pairs of test leads (banana plug to alligator clip)





Single power supply with multiple DC outputs

| Specifications          | Range                                    |
|-------------------------|--|
| Output Voltage (4)      | 0 to 30V, 0 to 30V, 3 to 6.5V,8 to 15V   |
| Output Current (4)      | 0 to 5A, 0 to 5A, 3A (fixed), 1A (fixed) |
| Load Voltage Regulation | ≤1x10-4 + 3mV                            |
| Line Voltage Regulation | ≤1x10 + 3mV                              |
| Load Current Regulation | ≤2x10+ 3mA                               |
| Line Current Regulation | ≤2x10 + 3mA                              |
| Ripple and Noise        | <0.5mVrms                                |
| Power                   | 100 to 240VAC,50/60Hz                    |
| Dimensions              | 10.2 x 6.3 x 14.5" (260 x 160 x 370mm)   |
| Weight                  | 26.5lbs (12kg)                           |



## **Ordering Information:**

382270 .....Quad Output DC Power Supply